



Color: ■ light gray Similar to illustration

Electrical data

| Ratings per IEC/EN | | Ex information | |
|-------------------------|-------|-------------------------|------|
| Nominal voltage (III/3) | 800 V | Rated current (Ex e II) | 20 A |
| Rated current | 25 A | | |

Physical data

| | |
|-------------------|------------------------|
| Width | 39.9 mm / 1.571 inches |
| Height | 4.1 mm / 0.161 inches |
| Depth | 19 mm / 0.748 inches |
| Jumper assignment | 1-8 |

Material data

| | |
|----------------------|--|
| Note (material data) | Information on material specifications can be found here |
| Color | light gray |
| Fire load | 0.02 MJ |
| Weight | 2.3 g |

Commercial data

| | |
|-----------------------|---------------|
| Product Group | 22 (TOPJOB S) |
| eCl@ss 10.0 | 27-14-11-40 |
| eCl@ss 9.0 | 27-14-11-40 |
| ETIM 8.0 | EC000489 |
| ETIM 7.0 | EC000489 |
| PU (SPU) | 25 pcs |
| Packaging type | Bag |
| Country of origin | DE |
| GTIN | 4055143691666 |
| Customs tariff number | 85366990990 |



| Environmental Product Compliance | |
|----------------------------------|------------------------|
| RoHS Compliance Status | Compliant,No Exemption |

Approvals / Certificates

Declarations of conformity and manufacturer's declarations



| Approval | Standard | Certificate Name |
|-------------------------------|----------|------------------|
| Railway WAGO GmbH & Co. KG | - | Railway Ready |

Downloads

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 2002-438


Download icon

| Documentation | | | |
|---------------|------------|-----------------|---------------|
| Bid Text | | | |
| 2002-438 | 19.02.2019 | xml 2.52 KB | Download icon |
| 2002-438 | 27.04.2017 | doc 24.00 KB | Download icon |


| CAD/CAE-Data | |
|--------------------------|-------------------------------|
| CAD data | CAE data |
| 2D/3D Models 2002-438 | EPLAN Data Portal 2002-438 |
| | WSCAD Universe 2002-438 |
| | ZUKEN Portal 2002-438 |

Installation Notes

Commoning




Insert push-in type jumper bar and push down until it hits backstop.




Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning



Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.


Commoning




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.