



Renk: ■ açık gri

Resime benzer

Elektrik Verisi

Ratings per IEC/EN

Anma gerilimi (III / 3)	800 V
Nominal akım	32 A

Ex information

Nominal akım (Ex e II)	30 A
------------------------	------

Geometrical Data

Width	60,1 mm / 2.366 inches
Height	4,1 mm / 0.161 inches
Depth	19 mm / 0.748 inches
Kademeli köprü genişliği	1-2-3-4-5-6-7-8-9-10

Material Data

Note (material data)

[Information on material specifications can be found here](#)

Renk	açık gri
Yangın yükü	0.038 MJ
Ağırlık	7.5 g

Ticari Veri

Product Group	22 (TOPJOB S)
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 8.0	EC000489
ETIM 7.0	EC000489
Pack. unit	25 Adet
SAP'den ambalaj tipi	Bag
SAP tesis 01'den menşei	DE
GTIN	4055143700634
SAP tesis 01'den gümrük tarifi no.	85366990990

Environmental Product Compliance

RoHS Compliance Status

Compliant, No Exemption

Onaylar / Sertifikalar

Declarations of conformity and manufacturer's declarations



Onay	Standart	Sertifika adı
Railway WAGO GmbH & Co. KG	-	Railway Ready

Dosya İndirme

Environmental Product Compliance

Compliance Search

Environmental Product
Compliance 2004-410

Documentation

Bid Text

2004-410	19.02.2019	xml 2.52 KB	
2004-410	28.04.2017	doc 23.50 KB	

CAD/CAE-Data

CAD data


2D/3D Models
2004-410

CAE data


EPLAN Data Portal
2004-410WSCAD Universe
2004-410ZUKEN Portal
2004-410

Montaj notları

Birbirine bağlama



Insert push-in type jumper bar and push down until it hits backstop.



Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Birbirine bağlama




Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.


Birbirine bağlama




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.